

SL-T3528PTB020-L190

PHOTO TRANSISTOR

DATA SHEET

SPEC. NO. : SZ19101902
DATE : 2021/11/01
REV. : A/1

Approved By:

Checked By:

Prepared By:



Absolute Maximum Ratings at Ta=25

Parameter	MAX.	Unit
Power Dissipation	100	mW
Collector-Emitter Voltage	30	V
Emitter-Collector Voltage	5	V
Moisture Sensitivity Level*1	5a	
Operating Temperature	-40 to + 85	
Storage Temperature	-40 to + 100	
IR Reflow Temperature	260 for 10 Seconds MAX.	

1. Storage and operating:

- (1). Storage requirements before vacuum bag opened: Temperature<30 , Humidity<65%RH;
- (2). Check air leakage and vacuum bag damage before opened. If there is any issue found, check the humidity indicator card immediately after bag opened:
 - a. If color changes on “10% circle” of the humidity indicator card only and not the circles of 20% and above, components can be used without additional handling;
 - b. If color changes on both 10% and 20% circles but not the circles of 30% and above, components must be dehumidified according to the conditions of bullet (5);
 - c. If color changes on 10%, 20%, and 30% circle or above, the product should be returned to the supplier for high temperature dehumidification;
- (3). After bag opened, manual soldering or reflow process must follow the following requirements:
 - a. Complete soldering / reflow within 24 hours;
 - b. Requirements of working environment: Temperature<30 , Humidity<60%RH;
- (4). If the working condition is outside (3)a or (3)b requirement, the components must be dehumidified according to the conditions of bullet (5);
- (5). Low temperature dehumidification: temperature 60±5 24 hours;
- (6). Shelf life: 30 days. If it's over 30 days from the production date on the package label, the components must be dehumidified according to the condition of bullet (5). If customer is unable to dehumidify, return components to LIGHT for dehumidification.

2. Caution in ESD:

Static Electricity and surge damages the LED. It is recommend to use a wris(ec)1.5(o:)-289.4()-289.5 ET

Qt Sta

The first part of the document discusses the importance of maintaining accurate records of all transactions. This includes not only sales and purchases but also any other financial activities that may occur during the course of the business. It is essential to ensure that all records are kept up-to-date and are easily accessible for review.

In addition, it is important to regularly reconcile the books to ensure that the records are accurate and complete. This involves comparing the records with bank statements and other external sources to identify any discrepancies. If any errors are found, they should be corrected immediately to avoid any potential issues.

The second part of the document focuses on the importance of maintaining accurate records of all transactions. This includes not only sales and purchases but also any other financial activities that may occur during the course of the business. It is essential to ensure that all records are kept up-to-date and are easily accessible for review.

In addition, it is important to regularly reconcile the books to ensure that the records are accurate and complete. This involves comparing the records with bank statements and other external sources to identify any discrepancies. If any errors are found, they should be corrected immediately to avoid any potential issues.

Finally, it is important to ensure that all records are kept in a secure and organized manner. This may involve using a dedicated accounting system or software to manage the records. It is also important to have a backup of the records to prevent any loss of data.



