

--	--	--	--

LIGHT



LG-IRM2B238KSF3

IC




PIN

RoHS REACH

2.7-5.5V

TTL CMOS

(MP3 MP4,)




		Min	Typ	Max			
Icc		No Input Signal		0.2	0.5	0.7	mA
L	0°	16	18	---	m		
	45°	8	9	---			
	45°	8	9	---			
f ₀		---	37.9	---	kHz		
BPF	fbw	fin=37.9kHz		---	7.0	---	kHz
BPF	fc	---	f ₀	+5	%		
Vol		Iosink=2.0mA		---	0.2	0.4	V
Voh		---		4.8	5.0	---	V
Av_max		fin=37.9kHz		60	64.5	68	dB
Rpul		---		---	50	---	k
Tpw		Vin =500 pp		400	600	800	μS

1m 40W

200±50Lux


Toshiba/NEC/Mitsubishi/RC5_Philips/Sony 12bit/Zenith/RC6/Continuous Code/Sony 15bit/
Sony 20bit/RCA/RCMM.




	Min.	Typ.	Max.	
V _{DD}	2.7	---	5.5	V
FM	---	37.9	---	kHz
Topr	---	25	---	

	V _{DD}	6.0	V
	Tstg	-40~100	
	Tsol	260±5 5S	

*




* $t_{pi} \geq 10/f_0$ is recommended for optimal function.



	260 ±5	5	20	20
	100PF, 1.5k , 4KV,	---	20	20
	10-50Hz/1min 1.5mm X Y Z/30min	30	20	20
	85 ±3	240	20	20
	-20 ±3	240	20	20
	85 85%	240	20	20
	-20 30 85 30	10	20	20
	2.5N 2	---	20	20

LIG




--	--	--	--

1

150mm × 190mm

500PCS



2

500pcs/

10 /

4 /

